

MAIN FEATURES

MINIATURE DESIGN

- > Gray coding 16 positions
- > Switching mode: Shorting
- 2.5 Ncm switching torque (remains consistent over life)
- **)** Body size $9 \times 9 \times 10$ mm
- > Lowest profile PCB to shaft center line: 4.65 mm
- > SMT reflow version available
- > Switching cycles 20,000
- > Optional IP68 front panel sealing
- ➤ Operating temperature range: -40 to +85°C

SWISS CLICK INDEXING SYSTEM™



PRODUCT VARIETY

- THT or SMT reflow (vacuum pick & place)
- Threaded or non-threaded bushing
- With end-stop or endless rotating
- Front panel sealing IP60 or IP68
- Various shaft types
- Tray or tape & reel packaging



For information about the SWISS CLICK INDEXING SYSTEM™ see chapter "Technical explanations"

POSSIBLE CUSTOMIZATIONS

- Shaft dimension and shape
- Others

TYPICAL APPLICATIONS

- Frequency and channel selection for two way radios
- Target aiming devices
- Other miniaturized mobile applications

¹ PREFERENCE TYPES SELECTION CHART

¹ For other types/options, see type key

PACKAGING	IP SEALING	PCB MOUNTING	BUSHING	SHAFT LENGHT	PART NUMBER WITH END-STOP	PART NUMBER ENDLESS ROTATING
Tray	IP60	SMT	Non-threaded	15.2 mm	C08S211ST	C08S221ST
			Threaded	15.2 mm	C08S111ST	C08S121ST
		THT	Threaded	18.0 mm	C08T111LT	C08T121LT
			Threaded	15.2 mm	C08T111ST	C08T121ST
	IP68	SMT	Threaded	15.2 mm	C08S311ST	C08S321ST
		THT	Threaded	18.0 mm	C08T311LT	C08T321LT
			Threaded	15.2 mm	C08T311ST	C08T321ST



SPECIFICATIONS

IANIC	

Resolution:	16 positions (22.5° indexing)
Switching torque (new condition):	2.5 Ncm (+/- 30%)
Rotational life:	20'000 cycles min.
Residual switching torque (end of life):	90% typical
End-Stop strength:	40 Ncm min.
Fastening torque of nut:	100 Ncm max.

ELECTRICAL DATA

Coding/output:	Gray
Switching mode:	Shorting
Contact resistance (new condition):	50 mΩ
Insulation resistance (new condition):	1 GΩ min. @ 500 VDC
Load current:	10 mA max. (resistive load, 15 VDC max.voltage)
Dielectric withstanding voltage:	500 VDC during 60 seconds (pin to pin, pin to housing)

MATERIAL DATA

Shaft:	Brass
Housing:	Zinc diecast with Miralloy plating, fiber enforced high performance plastic
Nut:	Brass
Contact system:	Alloy copper (Coding disk: nickel gold plated)
Soldering leads:	Alloy copper
O-rings:	NBR (nitrile), 70 shore, reflowable

ENVIRONMENTAL DATA

Operating/storage temperature range:	−40 to +85°C max.
IP sealing:	IP60, optional IP68 (2 bar, 1 h) shaft/front panel sealing
Vibration:	10 G _{rms} max. @ 10 to 2000 Hz
Flammability:	UL94-HB


PACKAGING QUANTITY

Tray:	50 pcs.
Tape & reel:	300 pcs.

SOLDERING CONDITIONS

Hand soldering:	280°C max. during 2 sec max.
Wave soldering:	280°C max. peak temperature during 2 sec max.

REFLOW PROFILE (COMPLIES WITH IPC/JEDEC J-STD-020C)



 $Temperatures \ or \ process \ durations \ exceeding \ rated \ maximum \ conditions \ may \ harm \ switch \ function.$

GRAY CODING

For information about Gray coding please see technical explanations at the end of the catalog.


www.elma.com 2/4




DRAWINGS


Tolerances unless otherwise specified DIN ISO 2768-1 (m)

SMT NON-THREADED






DRILLING DIAGRAM





View from component side of the PCB

FRONT PANEL CUT OUT




SMT THREADED






DRILLING DIAGRAM





View from component side of the PCB

FRONT PANEL CUT OUT




THT THREADED






DRILLING DIAGRAM




View from component side of the PCB


FRONT PANEL CUT OUT



TAPE & REEL PACKAGING

End of empty tape






Beginning of empty tape


EIA 481 Norm

SOLDERING SUPPORT DONUT



A soldering support donut is supplied on bushings with tape & reel packaging or tray packed SMT types. To be removed after soldering.

SLOTTED NUT



Part Number (50 pcs. bags):

- Brass: 4424-28

- Stainless steel (cross slot): 4424-31


FRONT PANEL CUT OUT



Spare Part Part Number (50 pcs. bags): - Brass: 4424-22




TYPE KEY



O-RING MOUNTING TOOL

Part Number: CO8RINGTL





- ① Slip the lubricated O-ring over the bushing.
- ② Slide the mounting tool over the bushing.
- 3 While pushing down the O-ring simultaneously rotate the mounting tool.